

HOMEWORK

- Section 4.2 - 9, 10, 15, 16, 19, 20, 23, 24, 26, 30, 50, 52, 54, 55, 56, 61, 65

SECTION 4.2 - SYSTEMS OF LINEAR EQUATIONS AND AUGMENTED MATRICES

Example 1. *Solve the system using an augmented matrix*

$$\begin{array}{rcrcrcrcl} 5x & - & 2y & = & 11 \\ 2x & + & 3y & = & \frac{5}{2} \end{array}$$

Solution. $x = 2, y = -\frac{1}{2}$

Example 2. *Solve the system using an augmented matrix*

$$\begin{array}{rcrcrcrcl} 2x & - & y & = & 4 \\ -6x & + & 2y & = & -12 \end{array}$$

Solution. *Begin by writing the augmented matrix, then just write the equivalences at every step*

$$\left[\begin{array}{cc|c} 2 & -1 & 4 \\ -6 & 3 & -12 \end{array} \right] \xrightarrow[\sim]{\frac{1}{2}R_1 \rightarrow R_1} \left[\begin{array}{cc|c} 1 & -\frac{1}{2} & 2 \\ -6 & 3 & -12 \end{array} \right]$$

$$\xrightarrow[\sim]{6R_1 + R_2 \rightarrow R_2} \left[\begin{array}{cc|c} 1 & -\frac{1}{2} & 2 \\ 0 & 0 & 0 \end{array} \right]$$

The bottom row contains all zeros. This means that the system is dependent and there are infinitely many solutions. Looking at the remaining equation

$$x - \frac{1}{2}y = 2$$

we can solve for x and get

$$x = \frac{1}{2}y + 2.$$

Setting $y = t$ for a parameter t , we get $x = \frac{1}{2}t + 2$ and so the solutions to this problem are points $(\frac{1}{2}t + 2, t)$ for any real number t .

Example 3. *Solve the system using an augmented matrix*

$$\begin{array}{rcrcrcrcl} 2x_1 & - & x_2 & = & -7 \\ x_1 & + & 2x_2 & = & 4 \end{array}$$

Solution. $x_1 = -2, x_2 = 3$

Example 4. *Solve the system using an augmented matrix*

$$\begin{array}{rrcr} -2x_1 & + & 6x_2 & = & 6 \\ 3x_1 & - & 9x_2 & = & -9 \end{array}$$

Solution. *For a parameter t , a solution is $x_1 = 3t - 3, x_2 = t$.*

Example 5. *Solve the system using an augmented matrix*

$$\begin{array}{rrcr} 2x_1 & - & x_2 & = & 6 \\ 4x_1 & - & 2x_2 & = & -1 \end{array}$$

Solution. *No solution*

Example 6. *Solve the system using an augmented matrix*

$$\begin{array}{rrcr} 2x & + & y & = & 1 \\ 4x & - & y & = & -7 \end{array}$$

Solution. $x = -1, y = 3$

Remark 1. *We mentioned above that the final form an augmented matrix with exactly one solution should look like*

$$\left[\begin{array}{cc|c} 1 & 0 & m \\ 0 & 1 & n \end{array} \right]$$

If the system has infinitely many solutions, it takes the form

$$\left[\begin{array}{cc|c} 1 & m & n \\ 0 & 0 & 0 \end{array} \right]$$

and if it has no solution, it takes the form

$$\left[\begin{array}{cc|c} 1 & m & n \\ 0 & 0 & p \end{array} \right]$$

where $p \neq 0$.

Example 7. *Solve the system using an augmented matrix*

$$\begin{array}{rrcr} x & - & 4y & = & -2 \\ -2x & + & y & = & -3 \end{array}$$

Solution. $x = 2, y = 1$

Example 8. *Solve the system using an augmented matrix*

$$\begin{array}{rcl} 2x & - & 3y = -2 \\ -4x & + & 6y = 7 \end{array}$$

Solution. *No solution*

Example 9. *Solve the system using an augmented matrix*

$$\begin{array}{rcl} 0.3x & - & 0.6y = 0.18 \\ 0.5x & - & 0.2y = 0.54 \end{array}$$

Solution. $x = 1.2, y = 0.3$

Example 10. *Solve the system using an augmented matrix*

$$\begin{array}{rcl} 2x & - & 4y = 2 \\ -3x & + & 6y = 3 \end{array}$$

Solution. *For a parameter t , the solution is $x = t, y = 2t - 1$*